

Effective Single HE₁₁ Mode Propagation in Silver-coated Teflon Tubes for THz applications

Navarro-Cia, Miguel; Melzer, Jeffrey E.; Harrington, James A.; Mitrofanov, Oleg

DOI:

[10.1109/USNC-URSI.2015.7303314](https://doi.org/10.1109/USNC-URSI.2015.7303314)

License:

Other (please specify with Rights Statement)

Document Version

Peer reviewed version

Citation for published version (Harvard):

Navarro-Cia, M, Melzer, JE, Harrington, JA & Mitrofanov, O 2015, Effective Single HE₁₁ Mode Propagation in Silver-coated Teflon Tubes for THz applications. in *Radio Science Meeting (Joint with AP-S Symposium), 2015 USNC-URSI*. Institute of Electrical and Electronics Engineers (IEEE), pp. 30. <https://doi.org/10.1109/USNC-URSI.2015.7303314>

[Link to publication on Research at Birmingham portal](#)

Publisher Rights Statement:

(c) 2015 IEEE. Personal use of this material is permitted. Permission from IEEE must be obtained for all other users, including reprinting/republishing this material for advertising or promotional purposes, creating new collective works for resale or redistribution to servers or lists, or reuse of any copyrighted components of this work in other works

General rights

Unless a licence is specified above, all rights (including copyright and moral rights) in this document are retained by the authors and/or the copyright holders. The express permission of the copyright holder must be obtained for any use of this material other than for purposes permitted by law.

- Users may freely distribute the URL that is used to identify this publication.
- Users may download and/or print one copy of the publication from the University of Birmingham research portal for the purpose of private study or non-commercial research.
- User may use extracts from the document in line with the concept of 'fair dealing' under the Copyright, Designs and Patents Act 1988 (?)
- Users may not further distribute the material nor use it for the purposes of commercial gain.

Where a licence is displayed above, please note the terms and conditions of the licence govern your use of this document.

When citing, please reference the published version.

Take down policy

While the University of Birmingham exercises care and attention in making items available there are rare occasions when an item has been uploaded in error or has been deemed to be commercially or otherwise sensitive.

If you believe that this is the case for this document, please contact UBIRA@lists.bham.ac.uk providing details and we will remove access to the work immediately and investigate.

Effective Single HE_{11} Mode Propagation in Silver-coated Teflon Tubes for THz applications

Miguel Navarro-Cía*^(1,2), Jeffrey E. Melzer⁽³⁾, James A. Harrington⁽³⁾, and Oleg Mitrofanov⁽²⁾

(1) Imperial College London, London SW7 2AZ, UK, m.navarro@imperial.ac.uk

(2) University College London, London WC1E 7JE, UK, o.mitrofanov@ucl.ac.uk

(3) Rutgers University, 607 Taylor Road, Piscataway, New Jersey 08854, USA, jaharrin@rutgers.edu

Developing single-mode waveguides for THz (i.e., 0.3 to 10 THz) applications with low attenuation encounters three major obstacles: in this range (i) dielectric and conductive losses are significant (D. Grischkowsky *et al.*, J. Opt. Soc. Am. B, 7, 2006, 1990), (ii) atmospheric absorption is high (Y. Yang *et al.*, IEEE Trans. THz Sci. Tech., 2, 406-415, 2012), and (iii) the dimensions required are challenging for standard fabrication techniques. Purged dielectric-lined hollow metallic waveguides offer one of the most promising solutions. They have been successfully fabricated with liquid flow polymer deposition for operation above 2 THz (O. Mitrofanov *et al.*, IEEE Trans. THz Sci. Tech., 1, 124-132, 2011) and by assembling dielectric and metallic cylinders for $\nu < 1$ THz (I.A. Tishchenko and A.I. Nosich, IEEE Microw. Magazine, 4, 32-44, 2003).

Recently, a versatile fabrication alternative based on silver-coating of polymer tubes has been demonstrated (J.E. Melzer *et al.*, Proc. SPIE, 8938, 89380I-1-10, 2014), but the fabricated waveguides have not been characterized yet. Here we study a 1 mm diameter 38 μm thick and a 2 mm diameter 120 μm thick polytetrafluoroethylene (commonly known by its brand name Teflon) tube coated with silver. Our analysis combines numerical calculations and near-field THz time-domain spectroscopy (M. Navarro-Cía *et al.*, Opt. Express, 21, 23748-23755, 2013). This measurement technique allows resolving modes in time, and thus, identifying single- or multi-mode propagation directly.

For the $\varnothing 1$ mm waveguide, we observe effective single-mode (HE_{11}) propagation in the band $1 < \nu < 1.6$ THz and multi-mode propagation elsewhere. The transmission loss estimated via a cut-back experiment is ~ 20 dB/m. This loss is substantially smaller than commercial single-mode hollow waveguides, e.g. rectangular waveguide WR-0.65 in which the theoretical transmission loss is between 258 to 406 dB/m at 1.1 and 1.7 THz, respectively. The loss of 20 dB/m is also lower than that in many recently proposed waveguides.

Teflon has relative low absorption coefficient and is easily found in different wall thicknesses and diameters. Hence, it was the choice for this work. However, other polymers with lower absorption coefficient like cyclic olefin copolymer may lead to experimental transmission loss below 10 dB/m according to our numerical work.